

433MHZ 工业遥控器



产品手册

可以广泛应用于所有自动门的无线解决方案

说明

433MHZ 工业遥控器是一款便捷、实用、可应用于所有自动门的无线解决方案，包括工业门、车库门及各种闸机。



产品性能

- 产品耐用，适用于工业环境。
- 在空旷区域，遥控距离可达100m。
- 每个发射器都有唯一的编码与接收器进行匹配。
- 根据不同的应用需求，可选择延迟或非延迟输出功能。
- 每个接收器可以配对100个发射器，并可以单独清除某一个发射器。
- 单个发射器绑定可被移除。
- 接收器具有4个独立的继电器。
- 4种遥控器可供选择（1，2，3或4个按钮）。
- 遥控器上的红色指示灯显示工作状态及电池寿命。
- 遥控器皮带夹可供选择。



1键遥控器



2键遥控器



3键遥控器



4键遥控器



标准接收器



遥控器皮带夹

应用

- 遥控工业门、车库门、各种闸机的理想解决方案。

安装便捷

- BEA 433MHZ 接收器可便捷地安装于各种自动门。

技术参数

频率	433MHz
发射无线电功率	≤7 dBm (遥控器)
功耗	32mA (遥控器) 40mA (接收器)
触点电压	1.0 A @ 30VDC
输入电压	3VDC (CR 2032 3V 电池 *2), 50,000 次 (遥控器) 9~30 VDC/AC (接收器)
工作温度	-30°C 至 70°C
单一接收器集成单元个数	100 个遥控器
调制方式	GFSK

参数如有变更，恕不另行通知。

DISCLAIMER This document as well as all other enclosed documents (quotation / specification / other) are provided «as is» without warranties of any kind, either expressed or implied, including but not limited to the implied warranties of merchantability, fitness for a particular purpose, or non-infringement. / Information is supplied upon the condition that the persons receiving it will make their own determination as to its suitability for their purposes prior to use. In no event will BEA be responsible for damages of any nature whatsoever resulting from the use of or reliance upon information from this document or the products to which the information refers. / BEA has the right without liability to change descriptions and specifications at any time. / Prices, shipping and availability are subject to change without prior notice.

